Note: This datasheet may be out of date. Please download the latest datasheet of NFE31PT222Z1E9# from the official website of Murata Manufacturing Co., Ltd.

http://www.murata.com/en/products/productdetail?partno=NFE31PT222Z1E9%23

"#" indicates a package specification code.

NFE31PT222Z1E9#







< List of part numbers with package codes >

NFE31PT222Z1E9B

NFE31PT222Z1E9K

NFE31PT222Z1E9L




Applications

Unsuitable	Please be sure to read and comply with	
Applications	these "Precautions for use."	
	Consumer equipment,Medical [Ask	
	Murata]	
	Please refer to Our Website and	
	specifications, etc. for information about	
Specific	the performance, functions, quality,	
Applications	management, and safety required for	
	the above applications, and use	
	Products after confirming the	
	performance and reliability of the actual	
	Product.	



Appearance & Shape







: Electrode

(in mm)

Packaging Information

Packaging	Specifications	Standard Packing Quantity
В	Bulk(Bag)	500
K	330mm Embossed Tape	8000
L	180mm Embossed Tape	2000



Features

The chip "EMIFIL" NFE31PT is a small size T-type circuit EMI suppression filter.

Features

- 1. Its large rated current of 6A and low voltage drop due to small DC resistance are suitable for DC power line use.
- 2. The feedthrough capacitor realizes excellent high frequency characteristics.
- 3. The structure incorporates built-in ferrite beads which minimize resonance with surrounding circuits.
- 4. 22 to 2,200pF lineups can be used in signal lines.

1 of 3

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering





NFE31PT222Z1E9#

Note: This datasheet may be out of date.

Please download the latest datasheet of NFE31PT222Z1E9# from the official website of Murata Manufacturing Co., Ltd.

http://www.murata.com/en/products/productdetail?partno=NFE31PT222Z1E9%23

"#" indicates a package specification code.



Specifications

SMD
1206
3.2mm
±0.35mm
1.6mm
±0.15mm
1.6mm
±0.15mm
-40°C to 85°C
0.034g
1
6A
25Vdc
62.5Vdc
1000ΜΩ
2200pF
±50%
3216

2 of 3

Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.



NFE31PT222Z1E9#


Note: This datasheet may be out of date


Please download the latest datasheet of NFE31PT222Z1E9# from the official website of Murata Manufacturing Co., Ltd.

http://www.murata.com/en/products/productdetail?partno=NFE31PT222Z1E9%23

"#" indicates a package specification code.








Insertion Loss Characteristics

Insertion Loss Characteristics (Main Items)



Equivalent Circuit

3 of 3

Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.